

Icoter Fiberconverter

Icoter i5800 Fiberconverter

On/Off-button.

LAN-ports.

Only port 1 is turned on.



Connect poweradapter here (12V/2A).

USB-ports (not used).

Phone-ports (not used).

Digital-TV and Radio outlet (CATV).

Troubleshoot using lights

On our fiberconverter there are a few statuslights.

If you're experiencing problems the lights are a good place to start troubleshooting.



- Link Activity** is green when communication is established.
- Link Activity** flashes green when there is internettraffic.
- Link Activity** is off when there is bad/no connection.
- Link status** is yellow when the port uses 1gb/s.
- Link status** is off when the port uses 10/100mb/s.
- GPON** is green when the fiber-converter has discovered and synchronised the signal.
- GPON** flashes green when synchronising.

- GPON** is red when no signal is found/no fiber is connected.
- CATV** is turned off when TV is deactivated.
- CATV** is green when TV is configured, turned on and has signal.
- CATV** is red when TV is turned on and configured but bad/no signal.
- All statuslights flashes green when starting the fiberconverter.
- All statuslights pulses green when updating.